

### MHTI-SUPERNODE FEATURES

- Fixture Agnostic up to 72 Watts Internal or Optional Remote Mount
- Engineered to Respond to the MHTi Peripheral Communication Network
- RS485 Protocol
- 0-10V External Driver Control
- 0-24V analog input
- Automatic Network Discovery
- Ultra High Electrical Conversion Efficiency of 90%
- Patented Single pair MHTi communication protocol for *MHTi-WS series* device support.
- Supports Optional MHTi Battery Backup
- Features a Dimming Range of 1% to 100%
- Dual channel color tuning fixture support
- Up to 8 programmable Inputs

### **GENERAL INFORMATION**

Warranty	5 Year Limited Warranty (Covers Standard Components)
Finish	White ABS
Construction	ABS/Aluminium

Certifications



### NODE POWER INPUT CHARACTERISTICS

Input Voltage	PoE Input: 40-60VDC DC IN: 24VDC to 60VDC
Peak Operating Power	80W max
Nominal Standby Power	1.35W
PoE Input Connection	Unshielded female RJ45 jack for CAT5e/6/6A cable to PoE PSE device.
Device Type	Class 2 electrical device

### **OUTPUT CHANNEL SPECIFICATIONS**

Output Channels	CH1 - CH8 (Individually Programmable)		
Driver Design	Programmable Constant Current (CC) or Constant Volt	age (CV)	
Output Voltage Range	<ul><li> 34V to 44V in Constant Current Mode</li><li> 12V to 48V in Constant Voltage Mode</li></ul>		
Output Current	<ul> <li>2A in Constant Current Mode, single channel</li> <li>5A in 12V Constant Voltage Mode, single channel</li> </ul>		
Rated Output Power	<ul> <li>72 Watts in Constant Current Mode (2 channels or more) and 60W per single channel.</li> <li>72 Watts in 48V and 36V Constant Voltage Mode (2 channels or more) and 72W per single channel</li> <li>67 Watts in 24V Constant Voltage Mode combine (2 channels or more) and 67W per single channel</li> <li>57 Watts in 12V Constant Voltage Mode combine (2 channels or more) and 57W per single channel.</li> </ul>	@ 50° C Ambient Temperatures	MHT Technologies Innovation Lab: 241 W. 37th St., Suite 1202, New York City, NY 10018 HQ & Warehouse: 1961 Richmond Ter, Staten Island, NY 10302 Tei: 718 524 4370 Www.mht-technologies.com
Protection	Individual LED driver channels have current limit and sh tion	nort circuit protec-	
Connections	2 TERM BLOCKS HDR 8POS VERT 5MM (4 channels ea	ach)	MHT Technologies, reserves the right to make any design changes for continuous improvement which will not affect the overall appearance or performance.





### **OUTPUT PROGRAMMING TABLE**

Model Number	Mode	Output Voltage	Maximum Current	Output Power
MHTI-SUPERNODE*	CC and CV Modes	<b>CV:</b> 12V to 48V	CV: 3.3A to 1.5A	<b>CV:</b> 40W to 70W
	Programmable	<b>CC:</b> 34V to 44V	CC: 2A	<b>CC:</b> 72W

Note: \*If any single channel in CH1 thru 4 or 5-8 is programmed as CV all channels in the group must be CV

### **INPUT SPECIFICATIONS**

Power Supply	24VDC @ 1 Amps for powering external sensors		
Termination Style	Screw Terminal/Plug to Board		
Termination Summary	<ul> <li>8 Inputs</li> <li>2 GND</li> <li>2 24VDC</li> </ul>		
Input Programming	8 Individual programmable input allows for localized output c the inspextor software.	ontrols, or cluster oriented	scene controls utilizing

### **OUTPUT CHANNEL POWER TABLE** @ 50° C ambient

MODE	CH1-8(W)	Single Channel (W)
сс	80	80
CV (48V)	75	75
CV (36V)	72	72
CV (24V)	65	65
CV (12V)	60	60

## H MHT Technologies

Innovation Lab: 241 W. 37th St., Suite 1202, New York City, NY 10018

HQ & Warehouse: 1961 Richmond Ter, Staten Island, NY 10302

#### Tel: 718 524 4370

www.mht-technologies.com



MHT Technologies, reserves the right to make any design changes for continuous improvement which will not affect the overall appearance or performance.

### SPRING CAGE CONNECTOR SPECIFICATIONS

24VDC	24VDC @ 1 Amps to power external devices such as the MHTi-EM-EXT to keep 0-10V line voltage fixture ON connected to an EM line voltage when there a PoE power lost. The power consumed from a device connected from 24VDC to GND is part of the output channels power budget.
0-10V	0-10V dimming control for line voltage fixtures
Input	Analog Input reads analog events from sensors or trigger devices, enabling the Node to take specific actions based on the received information.
485A and B	RS-485, half-duplex, 230.4k baud, 120 ohms impedance. Allows communication with compatible devices using this protocol.
GND	Circuit ground connection

### **ENVIRONMENTAL REQUIREMENTS**

Operating Temperature	0°C to 50°C
<b>Operating Environmental</b>	For dry or damp locations
Operating Humidity	10% to 80% RH non-condensing
Storage Temperature	-20°C to 85°C
Storage Humidity	5% to 95% RH non-condensing

### **DIMENSIONAL SPECIFICATIONS**

Dimension Overall	10.87"x3.895"x0.96"
Mounting Dimensions	10" offset mounting tabs
Origin	Assembled in the USA

#### **ORDERING INFO:** Sample Code - MHTi-SUPERNODE

Series

MHTI-SUPERNODE

# H MHT Technologies

Innovation Lab: 241 W. 37th St., Suite 1202, New York City, NY 10018

HQ & Warehouse: 1961 Richmond Ter, Staten Island, NY 10302

Tel: 718 524 4370

www.mht-technologies.com



MHT Technologies, reserves the right to make any design changes for continuous improvement which will not affect the overall appearance or performance.